

**CLAIMS**

1. A high duty cycle power converter (2) having a closed loop variable signal (12) current mode control characterised in that the variable signal (12) is changed by a derived signal (11) which is derived as a function of the difference between the desired duty cycle (7) and the measured duty cycle (6).  
5
2. A high duty cycle power converter (2) as claimed in claim 1, in which the derived signal (11) is referenced with the variable signal (12) to provide a control signal (13) in a controller (5) to change the variable signal (12) to operate the current mode control.  
10
3. A high duty cycle power converter (2) as claimed in any preceding claim, comprising means for measuring the measured duty cycle (6) from switching elements of the input switching stage (3) of the power converter (2) by measuring the on time interval of each switching element during a preset time interval.  
15
4. A high duty power converter (2) as claimed in any preceding claim, in which the desired duty cycle is set on a deadtime requirement consistent with substantially lossless switching.  
20
5. A high duty power converter (2) as claimed in claim 4, in which the desired duty cycle is fixed in the range 90% to 99%.  
25
6. A high duty power converter (2) as claimed in claim 4, in which means are provided to change the desired duty cycle having regard to operating parameters.  
30
7. A high duty power converter (2) as claimed in claim 6, in which the operating parameter is the load on the high duty power converter (2).

8. A high duty power converter (2) as claimed in any preceding claim, in which means are provided to deliver a signal analogous to the measured duty cycles.
- 5 9. A high duty cycle power converter (2) as claimed in claim 8, in which the means comprises an averaging circuit (8).
- 10 10. A high duty cycle power converter (2) as claimed in any preceding claim, in which the controller (5) comprises an error amplifier (9) to compare the desired duty cycle signal (7) with the measured duty cycle (6) signal to provide the derived signal (11).
- 15 11. A high duty cycle power converter (2) as claimed in any preceding claim, in which the controller (5) to operate the current mode control comprises means for generating drive signals (15, 16) from the control signal (13) to modify the duty cycle of the input switching elements of the input switching stage (3).
- 20 12. A high duty power converter (2) as claimed in any preceding claim, in which the output of the power converter (2) is used to clamp the voltage of the power converter (2).
- 25 13. A high duty cycle power converter (2) as claimed in claim 12, wherein a diode (23) is connected in parallel with an output inductor (21) of the power converter (2) to clamp the voltage of the power converter.
- 30 14. A high duty cycle power converter (2) as claimed in claim 13, in which a resistor (24) is placed in series with the diode (23) and connected in parallel with the output inductor (21).
15. A high duty cycle power converter (2) as claimed in any preceding claim, in which there is provided means to adjust the effective duty cycle to compensate for ripple voltages.

16. A high duty cycle power converter (2) as claimed in claim 15, in which there is provided a saturable reactor (31a, 31b) connected to output switching elements of the output switching stage (4) of the power converter to adjust effective duty cycle of the power converter (2).
- 5
17. A high duty cycle power converter (2) as claimed in claim 16, in which the saturable reactor (31a, 31b) is provided with a controllable reset condition to provide a delay for the output switching elements to adjust the effective duty cycle of the power converter.
- 10
18. A high duty cycle power converter (2) as claimed in any of claims 15 to 17, comprising a reset winding having a control signal derived from a closed loop monitoring of the output voltage.
- 15
19. A high duty cycle power converter (2) as claimed in any of claims 15 to 17, in which the means to adjust the effective duty cycle comprises a reset winding having a control signal obtained from a prediction of the needed ripple voltage requiring cancellation.
- 20
20. A high duty cycle power converter (2) as claimed in any preceding claim, in which a separate auxiliary winding (56, 57) is connected to the primary winding (51) of the converter to provide an auxiliary gate drive signal to switches (52, 55).
- 25
21. A high duty cycle power converter (2) as claimed in any preceding claim, in which a clamp circuit (58, 59) is connected to the midpoint of the primary winding (51).
- 30
22. A method of controlling a high duty cycle power converter having a variable signal operated current mode control comprising the steps of:-

measuring the duty cycle of the power converter,

comparing a desired duty cycle with the measured duty cycle to  
provide a derived signal;

5           referencing the derived signal with a current sense signal from the  
power converter to provide a control signal; and

generating drive signals from the control signal to implement a  
closed loop current mode control in the power converter.

10

Dk\Prelim 13\PSO204amendmar14nontrack

15

20

25

30

35

40